Paramétrage du scanner de code-barre Zebra DS2208 pour utilisation avec AlmaPro

DS2208





Table des matières

Téléchargement de l'utilitaire 123Scan	1
Mise à jour du logiciel du scanner de code-barre	2
Configuration du scanner de code-barre dans 123Scan	4

Téléchargement de l'utilitaire 123Scan

Cliquez sur le lien pour télécharger l'utilitaire 123Scan :

https://www.zebra.com/fr/fr/support-downloads/software/scanner-software/123scan-utility.html

Cliquez ici :				
Téléchargements				
Logiciel essentiel au fonctionnement et à la connexion de cet appareil.				
CATEGORIES				
a for a set of the set				
NOM \$	DATE	\$	\mathbf{h}	
123SCAN Utility For Windows 10 (32 And 64BIT) And Windows 11 (64BIT)	Août 2024	1		▶~

Puis, sélectionnez l'installateur pour Windows 64 bits :

NOM \$			DATE ≑
123SCAN Utility For W 64BIT) And Windows 1	indows 10_(32 And 1_(64BIT)		Août 2024
6.00.0022 2 fichiers Date de sortie : 0	Octobre 2024		
VERSION	6.00.0022 123Scan Scanner Configuration Utility Release Notes		
FICHIERS	Zebra_123Scan_(32bit)_v6.00.0022.exe 123Scan pour Windows 32bit	532 MB	TÉLÉCHARGEMENT
	Zebra_123Scan_(64bit)_v6.00.0022.exe 123Scan pour Windows 64bit	539 MB	TÉLÉCHARGEMENT

L'installation est simple, il suffit de cliquer quelques fois sur « Suivant » et « Terminer ».



Mise à jour du logiciel du scanner de code-barre

Actions -	THE THE TY				60
Actions •					
What do you	u want to do?	2			
Create ne	w configura	tion file			✓ 123Scan Overview
	shi contigura				How to Videos
Load exis	ting configu	ration file			
Clone/mo	difu mu conu	pacted scopper settin	ac.		
Cionernio	uny my com	lected scariner settin	ys		
Update so	canner firmw	/are			
Recent files		A CONST			
Туре	Model	Name	Ver.	Date modified	File name and location
Config File	DS2208	Factory Default	001	07-mars-2023	Config File_DS2208_Factory Default_2023.03.07.scncfg
Config File	DS2208	Factory Default	001	07-mars-2023	Config File_DS2208_Factory Default_2023.03.07.scncfg
More Files					
🔍 123Scan Up	odater: Your utility	and plug-ins are up-to-date as	of 07/03/2023,	14:06. View updat	e history Supported scanners Release notes Check for updates
e firmware					

Select alternate firmware Select alternate firmware During firmware update, your scanner settings can be changed. Choose from the options below: Option 1 – Load firmware BUT Keep current settings (Recommended) Option 2 – Load firmware AND Reset to factory defaults Option 3 – Load firmware THEN Load other settings Firmware : CAADFS00-004-R00 - Jan 2022 Support for supply chain material changes		Serial number: 22116010552663 Existing: Release 017 - 2022.10.11 (CAADES00-005-R00) Update to: Release 017 - 2022.10.11 (CAADES00-005-R00) Select alternate firmware During firmware update, your scanner settings can be changed. Choose from the options below: Option 1 – Load firmware BUT Keep current settings (Recommended) Option 2 – Load firmware THEN Load other settings	 Kelease Notes: ************************************	
DISCOVERED SCANNER LIST	DISCOVERE	D SCANNER LIST		CLOSE





Update firmware		×
Confirm that you want to u DS2208-COMMOI Serial number: 221160103 Existing: Release 017 Update to: Release 017	Ipdate the following scanner N SR MODELS 552663 - 2022.10.11 (CAADES00-005-R00) - 2022.10.11 (CAADES00-005-R00) Step 3 - Rebooting scanner, please wait	
Update firmware DISCOVERED SCANNER LIST		CLOSE

Update firmware	×
Confirm that you want to update the following scanner	
DS2208-COMMON SR MODELS Serial number: 22116010552663 Existing: Release 017 - 2022.10.11 (CAADES00-005-R00)	
Update to: Release 017 - 2022.10.11 (CAADES00-005-R00)	
Upload complete	
It is now safe to disconnect the scanner.	
Update firmware	
DISCOVERED SCANNER LIST	UPDATE ANOTHER CLOSE



Configuration du scanner de code-barre dans 123Scan

						0	~
Start Dat	a view					()	L
🍓 Actions 🔻							
Nhat do voi	uwant to do?	,					
Create ne	w configura	tion file			23Scan Overview		
					How to Videos		
Load exis	ting configu	ration file					
Clone/mo	dify my coni	nected scanner setting	gs				
Update so	canner firmw	vare					
	canner firmw	/are					
Update so Recent files Type	Canner firmw Model	vare	Ver.	Date modified	File name and location		
Update so Recent files Type Config File	Model DS2208	Vare Name Factory Default	Ver. 001	Date modified 07-mars-2023	File name and location Config File_DS2208_Factory Default_2023.03.07.sc	ncfg	
Update so Recent files Type Config File Config File	Model DS2208 DS2208	Vare Name Factory Default Factory Default	Ver. 001 001	Date modified 07-mars-2023 07-mars-2023	File name and location Config File_DS2208_Factory Default_2023.03.07.sc Config File_DS2208_Factory Default_2023.03.07.sc	ncfg	
Opdate so Recent files Type Config File Config File	Model DS2208 DS2208	Vare Name Factory Default Factory Default	Ver. 001 001	Date modified 07-mars-2023 07-mars-2023	File name and location Config File_DS2208_Factory Default_2023.03.07.sc Config File_DS2208_Factory Default_2023.03.07.sc	ncfg	
Update so Recent files Type Config File Config File	Model DS2208 DS2208	Vare Name Factory Default Factory Default	Ver. 001 001	Date modified 07-mars-2023 07-mars-2023	File name and location Config File_DS2208_Factory Default_2023.03.07.sc Config File_DS2208_Factory Default_2023.03.07.sc	ncfg	
Update so Recent files Type Config File Config File	Model DS2208 DS2208	Vare Name Factory Default Factory Default	Ver. 001 001	Date modified 07-mars-2023 07-mars-2023	File name and location Config File_DS2208_Factory Default_2023.03.07.sc Config File_DS2208_Factory Default_2023.03.07.sc	ncfg	
Update so Recent files Type Config File Config File	Model DS2208 DS2208	Vare Name Factory Default Factory Default	Ver. 001 001	Date modified 07-mars-2023 07-mars-2023	File name and location Config File_DS2208_Factory Default_2023.03.07.sc Config File_DS2208_Factory Default_2023.03.07.sc	ncfg	
Update so Recent files Type Config File Config File	Model DS2208 DS2208	Vare Name Factory Default Factory Default	Ver. 001 001	Date modified 07-mars-2023 07-mars-2023	File name and location Config File_DS2208_Factory Default_2023.03.07.sc Config File_DS2208_Factory Default_2023.03.07.sc	ncfg	
Update so Recent files Type Config File Config File	Model DS2208 DS2208	Are Name Factory Default Factory Default	Ver. 001 001	Date modified 07-mars-2023 07-mars-2023	File name and location Config File_DS2208_Factory Default_2023.03.07.sc Config File_DS2208_Factory Default_2023.03.07.sc	ncfg	

الله. 123Scan	_ 🗆 ×
Barcodes - Preferences Too	ols 👻 Help 👻
Start Data view Factory Default 🛞	
🖏 Actions 👻 🖆 Save file to PC 🛛 🖴 Print bar code 🛛 🚒 Load to scanner 🔯 Email Bar Code to Phone 🗟 Print/Save parameters 🔛 How to video	
Model List Plug-in Name Configuration file summary	
Release Notes Configuration name: Factory Default View	v / Edit
DS2208-COMMON SR MODELS-017 USB (default) Keyboard Wedge IBM-RS485	//Edit
Start comiguration wizard >> Symbologies (bar code types) Factory default settings View	v / Edit
Modify Data No rules	v / Edit
Imaging Factory default settings	v / Edit
General View Factory default settings	v / Edit
Printing Options View	v / Edit



t, 123Scan				Barcodes 🔻	E	×
Start Data view Factory Def	ault 🛞			Darodado	() () ()	• •
🖏 Actions 👻 🖆 Save file to PC 🎍	Print bar code	🗧 Load to scanner	Email Bar Code to Phone	🖹 Print/Save parameters	How to video	
Model List Plug-in Name Release Notes App Developer Report DS2208-COMMON SR MODEL S-017	Name and I Please be sure to notes and give the Configuration name:	notes give your settings a e configuration name AlmaPro	configuration name. You can al a version number. What is this?	so add		
Name and notes Name:Factory Default Notes: Cable connection USB (default) Keyboard Wedge	Notes:			<u>م</u>		
Symbologies (bar code types) Factory default settings Modify Data No rules		500 of 500 chara	cters remaining			
5. Imaging Factory default settings 6. General Factory default settings						
7. Printing Options 8. Load and print						
< Back Next >	Done	Cancel		Search for a parameter		





123Scan		
12000411		Barcodes - Preferences Tools - Help
Start Data view AlmaPro		۵ ک
🖏 Actions 👻 🖆 Save file to PC 🖉	Print bar code 🛛 🏾 🗮 Load to scanner 🛛 💐 Email Bar Co	de to Phone 🔋 Print/Save parameters 📲 How to video
Model List Plug-in Name Release Notes	Change your bar code settings Your scanner is already set up to recognize the most com select a symbology (bar code type) from the drop-down bi	Disable all symbologies Print sample bar codes mon types of bar codes. To modify your decoding options, elow.
DS2208-COMMON SR MODELS-017	DataMatrix v	
Name:AlmaPro Notes:	Data Matrix Data Matrix Inverse Autodetect	
2. Cable connection USB (default) Keyboard Wedge IBM-RS485	GS1-Datamatrix	
3. Symbologies (bar code types) Factory default settings		
4. Modify Data No rules		
5. Imaging Factory default settings		
6. General Factory default settings		
7. Printing Options		
8. Load and print		
 Parameters changed from factory default 		
< Back Next >	Done Cancel	Search for a parameter





123Scan		_ 🗆 ×
12000011		Barcodes - Preferences Tools - Help -
Start Data view AlmaPro		• •
🖏 Actions 👻 🖆 Save file to PC 🛔	Print bar code 🛛 🌋 Load to scanner 🛛 💐 Email Bar Code to Phone	e 🖹 Print/Save parameters 🔛 How to video
Model List Plug-in Name Release Notes App Developer Report	Change image settings The parameters below pertain to imaging settings. Click on blue links below for faster parameter list navigation.	
MODELS-017	Signature Capture Signature Capture Signature Capture JPEG ~	
Notes: 	Signature Capture 8 BPP v Bits Per Pixel	
Symbologies (bar code types) Factory default settings Modify Data	Signature Capture	
5. Imaging Factory default settings	Signature Capture	
6. General Factory default settings - 7. Printing Options	Signature Capture 65 🗼	
8. Load and print		
 Parameters changed from factory default 		
< Back Next >	Done Cancel	Search for a parameter

Mit. 123Scan		_ 🗆 ×
14		Barcodes - Preferences Tools - Help -
Start Data view AlmaPro		@ D 😔
🖏 Actions 👻 🖆 Save file to PC 🖉	Print bar code 🛛 🌠 Load to scanner 🛛 💐 Email Bar Code to Phone	Print/Save parameters 🔛 How to video
Model List Plug-in Name Release Notes App Developer Report	General The parameters below are general scanner settings and user preference Click on blue links below for faster parameter list navigation.	ies.
DS2208-COMMON SR MODELS-017	Power Power System Beeper Power Mode Continuous Or	 ■
Name:AlmaPro Notes: 2. Cable connection USB (default) Keyboard Wedge	Time Delay To Low 1 Hour × Power	
IBM-RS485 3. Symbologies (bar code types) Factory default settings 4. Modify Data	System Parameter Scanning	
No rules 5. Imaging Factory default settings	Allowed	
6. General Factory default settings 7. Printing Options	Type A	
8. Load and print	Country Code Default for a s Page	et Country Type 👻
 Parameters changed from factory default 	Unicode Output Universal Outp Control	out ∽
< Back Next >	Done Cancel	Search for a parameter



Si vous souhaitez supprimer les bips du scanner, vous pouvez indiquer les paramètres ci-dessous :



th. 123Scan		🖬 🗙
Start Data view AlmaPro	8	() () ()
🖏 Actions 👻 🖆 Save file to PC	Print bar code 🛛 🌋 Load to scanner 🛛 💐 Email Bar Code to Phone	e 🖹 Print/Save parameters 🔛 How to video
Model L Plug-in Nar Release Not App Developer Repo DS2208-COMMON SR MODELS-017	st General The parameters below are general scanner settings and user prefere Click on blue links below for faster parameter list navigation. Power System	nces.
Name:AlmaPro Notes:	Beeper Beeper Volume * Low *	
2. Cable connection USB (default) Keyboard Wedge IBM-RS485	Beeper Tone * OFF *	
3. Symbologies (bar code types) Factory default settings 4. Modify Data	Beep After Good Decode *	
No rules 5. Imaging Factory default settings	Beeper Duration * Short *	
6. General Factory default settings	Suppress Power Up 🔀 Beeps ^	
7. Printing Options 8. Load and print		Ē
A Parameters changed from factory default		
< Back Next >	Done Cancel	Search for a parameter



t. 123Scan						_ 🗆 ×
12000411				Barcodes 👻	Preferences T	ools 👻 Help 👻
Start Data view AlmaPro	0					
🖏 Actions 👻 🖺 Save file to PC 🔓	Print bar code 🛛 🏾 🗮 Loa	d to scanner 🛛 😽 Email B	ar Code to Phone	🖹 Print/Save parameters	🔛 How to vide	5
Model List Plug-in Name Release Notes App Developer Report	Printing Options The parameters below a	re print and paper options				
DS2208-COMMON SR MODELS-017	Default Options Page Setup Barcode Layout Parameter Scanning	Default Options Start programming barcode with	 No Defaults Set Factory I Set Defaults 	Defaults		
1. Name and notes Name: AlmaPro Notes: 2. Cable connection USB (default) Keyboard Wedge		Print only parameters changed from defaults				U
IBM-RS485 3. Symbologies (bar code types) Factory default settings 4. Modify Data		Erase All Rules	×			
5. Imaging Factory default settings		Page Setup Paper Size	Letter (8.5 x 11	.0 in. 216 x 280 mm) ~		
6. General A Custom settings 7. Printing Options		Orientation	 Portrait Landagana 			
8. Load and print		Margin Top	100			
-		Margin Dottom	x0.01 Inches			-
< Back Next >	Done	ancel		Search for a parameter		

Start Data view AlmaBro		
Actions	Print bar code 👔 Load to scanner 🥰 Email Bar Code to Prione	PhiloSave parameters
Model List Plug-in Name Release Notes App Developer Report	Load and print Choose from the options below to program your scanner	
DS2208-COMMON SR MODELS-017	Save to PC	
Name:AlmaPro Notes:	Print bar code	
2. Cable connection USB (default) Keyboard Wedge IBM-RS485	Load to scanner 🛛 🖌	
3. Symbologies (bar code types) Factory default settings	Email bar code to phone	
4. Modify Data No rules	Email electronic config file	
5. Imaging Factory default settings 8. General ^A	Print/export parameter report	
Custom settings 7. Printing Options		
8. Load and print		
A Parameters changed from factory default		
	D	



Load configuration	×
DS2208-COMMON SR MODELS Firmware version: Release 017 - 2022.10.11 (CAADES00-005-R00) DS2208 model list	
1 compatible scanner(s) found for your configuration.	
Clicking on a scanner above will begin the loading for that scanner. You can click the FLASH/BEEP icon within a row to find that particular scanner. Or to initiate the loading of all scanners. click the IOAD TO ALL SCANNERS button above.	
DISCOVERED SCANNER LIST	SE
oad configuration	×
DS2208-COMMON SR MODELS Firmware version: Release 017 - 2022.10.11 (CAADES00-005-R00) DS2208 model list	
1 compatible scanner(s) found for your configuration. LOAD TO ALL SCANNERS	
Uploading AlmaPro	

DISCOVERED SCANNER LIST



CLOSE

Load configuration	×
DS2208-COMMON SR MODELS Firmware version: Release 017 - 2022.10.11 (CAADES00-005-R00) DS2208 model list	
1 compatible scanner(s) found for your configuration. LOAD TO ALL SCANNERS	
Upload complete. 1 of 1 scanner(s))
100 %	J
LOAD MORE DISCOVERED SCANNER LIST	CLOSE

